




Oregon Scientific Meep! 4.0 Motherboard Replacement

Follow the steps in this guide to replace the Motherboard of your Oregon Scientific Meep! 4.0

Written By: Lauren Milici



INTRODUCTION


By following the steps in this guide in order, you will be able to remove and replace the broken motherboard of your Oregon Scientific Meep! 4.0 tablet.



TOOLS:

- [Screwdriver](#) (1)
 - [Soldering Station](#) (1)
 - [iFixit Opening Tools](#) (1)
-

Step 1 — Oregon Scientific Meep! 4.0 Disassembly





- Use a screwdriver to remove the four 7.0 mm Philips #00 screws from the back of the device.

Step 2




- Use a plastic opening tool to detach the clips on the inside of the device.

Step 3 — Motherboard




- Use a soldering station to disconnect any wires attached to the motherboard.

Step 4



- Use a screwdriver to unscrew the three 4.0 mm Philips #00 screws holding the motherboard in place.

Step 5



- Use a plastic opening tool to release the ribbon cables surrounding the motherboard.

To reassemble your device, follow these instructions in reverse order.

This document was last generated on 2017-06-25 03:18:54 AM.